

Parts List

001 Stator Body – Foot Mount*	010 Cable Glands*
002 Stator Body – Flange Mount*	011 Key*
003 Drive End – End Shield	012 Drive End Bearing
004 B14 Flange (Up to 132 frame)	013 Non Drive End Bearing
005 B5 Flange	014 Non Drive End – End Shield
006 Drive End Oil Seal	015 Cooling Fan
007 Terminal Box Lid	016 Fan Clamping Bush*
008 Terminal Box Gasket	017 Fan Cover
009 Terminal Block	018 Left Foot*
	019 Right Foot*

* For all aluminium multi mount motors

Replacement parts are stocked for motors up to 200 frame

To Order Spare Parts for the FM:P Range:

FIRST THREE DIGITS:

Motor material and efficiency

Code	Range	Material
170	Standard Efficiency	Aluminium
171	Standard Efficiency	Cast Iron
172	Premium Efficiency	Aluminium
173	Premium Efficiency	Cast Iron

FOURTH DIGIT:

Frame size

Code	Frame
A	56
B	63
C	71
D	80
E	90
F	100
G	112
H	132
J	160
K	180
L	200
M	225
N	250
P	280
R	315
S	355
T	400
U	450
V	500
W	560

FIFTH DIGIT:

When ordering spare parts always use 9 as the fifth digit.

SIXTH, SEVENTH & EIGHTH DIGIT:

Please select relevant item number from the spare parts list above.



Fenner FM:P Bearings

Frame Size	Poles	Driving End		Non Driving End		
		Ball Bearing	NU Bearing	Ball Bearing	Regreasable Bearings	V1 Mounting
80	2 - 10	6204 2RZ	–	6204 2RZ	–	6204 2RZ
56	2 - 4	6201 2RZ	–	6201 2RZ	–	6201 2RZ
63	2 - 4	6201 2RZ	–	6201 2RZ	–	6201 2RZ
71	2 - 6	6202 2RZ	–	6202 2RZ	–	6202 2RZ
80	2 - 8	6204 2RZ	–	6204 2RZ	–	6204 2RZ
90	2 - 8	6205 2RZ	–	6205 2RZ	–	6205 2RZ
100	2 - 8	6206 2RZ	–	6206 2RZ	–	6206 2RZ
112	2 - 8	6206 2RZ	–	6206 2RZ	–	6206 2RZ
132	2 - 8	6208 2RZ	–	6208 2RZ	–	6208 2RZ
160	2 - 12	6309 ZZ C3	NU 309	6309 ZZ C3	6309 C3	6309 ZZ C3
180	2 - 12	6311 ZZ C3	NU 311	6311 ZZ C3	6311 C3	6311 ZZ C3
200	2 - 12	6312 ZZ C3	NU 312	6312 ZZ C3	6312 C3	6312 ZZ C3
225	2 - 12	6313 ZZ C3	NU 313	6313 ZZ C3	6313 C3	6313 ZZ C3
250	2 - 12	6314 ZZ C3	NU 314	6314 ZZ C3	6314 C3	6314 ZZ C3
280	2	–	NU 314	–	6314 C3	6314 C3-EQ*
280	4 - 12	–	NU 317	–	6317 C3	6317 C3-EQ*
315	2	–	NU 317	–	6317 C3	6317 C3-EQ*
315	4 - 12	–	NU 319	–	6319 C3	6319 C3-EQ*
355	2	–	NU 317	–	6317 C3	7317 B
355	4 - 12	–	NU 322	–	6320 C3	7320 B
400	2	–	NU 317	–	6317 C3	7317 B
400	4 - 12	–	NU 326	–	6326 C3	7326 B
450	2	–	NU 319	–	6319 C3	7319 B
450	4 - 12	–	NU 328	–	6328 C3	7328 B
500	4 - 12	–	NU 330	–	6330 C3	7330 B
560	4 - 12	–	NU 334	–	6330 C3	7330 B

*EQ = SKF Explorer Quality
 Bold type indicates standard bearings.